

## Features

- High Gain: 23 dB
- P1dB: 30 dBm
- P<sub>SAT</sub>: 33 dBm
- IM3 Level: -22 dBc @ P<sub>OUT</sub> 27 dBm/tone
- Power Added Efficiency: 24% at P<sub>SAT</sub>
- Lead-Free 5 mm AQFN 32-lead Package
- RoHS\* Compliant

## Description

The MAAP-011246 is a 2 Watt, 4-stage power amplifier assembled in a lead-free 5 mm 32-lead AQFN plastic package. This power amplifier operates from 27.5 to 31.5 GHz and provides 23 dB of linear gain, 2 W saturated output power and 24% efficiency while biased at 6 V.

The MAAP-011246 can be used as a power amplifier stage or as a driver stage in higher power applications. This device is ideally suited for VSAT and 28 GHz PTP applications.


This product is fabricated using a GaAs pHEMT process which features full passivation for enhanced reliability.

## Ordering Information<sup>1,2</sup>

| Part Number        | Package        |
|--------------------|----------------|
| MAAP-011246-TR0500 | 500 Piece Reel |
| MAAP-011246-1SMB   | Sample Board   |

1. Reference Application Note M513 for reel size information.
2. All sample boards include 3 loose parts.

## Functional Schematic



## Pin Configuration<sup>3</sup>

| Pin #   | Function        | Pin #               | Function        |
|---------|-----------------|---------------------|-----------------|
| 1       | Ground          | 20                  | Ground          |
| 2       | No Connection   | 21                  | RF Output       |
| 3       | Ground          | 22                  | Ground          |
| 4       | RF Input        | 23                  | No Connection   |
| 5 - 7   | No Connection   | 24, 25              | Ground          |
| 8, 9    | Ground          | 26                  | Drain Voltage 4 |
| 10      | Gate Voltage    | 27, 28              | Drain Voltage 3 |
| 11      | Gate Voltage    | 29                  | Drain Voltage 2 |
| 12 - 14 | No Connection   | 30                  | No Connection   |
| 15      | Drain Voltage 4 | 31                  | Drain Voltage 1 |
| 16, 17  | Ground          | 32                  | Ground          |
| 18, 19  | No Connection   | Paddle <sup>4</sup> | Ground          |

3. MACOM recommends connecting all No Connection (N/C) pins to ground.
4. The exposed pad centered on the package bottom must be connected to RF, DC and thermal ground.

\* Restrictions on Hazardous Substances, compliant to current RoHS EU directive.

**Electrical Specifications: Freq. = 30 GHz, T<sub>A</sub> = +25°C, V<sub>D</sub> = 6 V, Z<sub>0</sub> = 50 Ω**

| Parameter              | Test Conditions                                | Units | Min. | Typ. | Max. |
|------------------------|--|-------|------|------|------|
| Gain                   | P <sub>IN</sub> = 0 dBm                        | dB    | 19   | 22   | —    |
| P <sub>OUT</sub>       | P <sub>IN</sub> = 15 dBm                       | dBm   | 31.5 | 33   | —    |
| IM3 Level              | P <sub>OUT</sub> = 27 dBm / tone               | dBc   | —    | -22  | —    |
| Power Added Efficiency | P <sub>SAT</sub> (P <sub>IN</sub> = 15 dBm)    | %     | —    | 24   | —    |
| Input Return Loss      | P <sub>IN</sub> = -20 dBm                      | dB    | —    | 10   | —    |
| Output Return Loss     | P <sub>IN</sub> = -20 dBm                      | dB    | —    | 14   | —    |
| Quiescent Current      | I <sub>DQ</sub> (see bias conditions, page 4 ) | mA    | —    | 900  | —    |
| Current                | P <sub>SAT</sub> (P <sub>IN</sub> = 15 dBm)    | mA    | —    | 1450 | —    |

## Maximum Operating Ratings

| Parameter                           | Rating         |
|-------------------------------------|----------------|
| Input Power                         | 15 dBm         |
| Junction Temperature <sup>5,6</sup> | +160°C         |
| Operating Temperature               | -40°C to +85°C |

- Operating at nominal conditions with junction temperature  $\leq +160^\circ\text{C}$  will ensure MTTF  $> 1 \times 10^6$  hours.
- Junction Temperature (T<sub>J</sub>) = T<sub>C</sub> +  $\Theta_{JC} * ((V * I) - (P_{out} - P_{in}))$   
Typical thermal resistance ( $\Theta_{JC}$ ) = 8°C/W.
  - For T<sub>C</sub> = +25°C,  
T<sub>J</sub> = +79°C @ 6 V, 1.45 A, P<sub>OUT</sub> = 33.0 dBm, P<sub>IN</sub> = 15 dBm
  - For T<sub>C</sub> = +85°C,  
T<sub>J</sub> = +136°C @ 6 V, 1.34 A, P<sub>OUT</sub> = 32.4 dBm, P<sub>IN</sub> = 15 dBm

## Handling Procedures

Please observe the following precautions to avoid damage:

## Static Sensitivity


These electronic devices are sensitive to electrostatic discharge (ESD) and can be damaged by static electricity. Proper ESD control techniques should be used when handling these HBM Class 1A devices.

## Absolute Maximum Ratings<sup>7,8</sup>


| Parameter                         | Absolute Maximum |
|-----------------------------------|------------------|
| Input Power                       | 20 dBm           |
| Drain Voltage                     | +6.5 V           |
| Gate Voltage                      | -3 to 0 V        |
| Junction Temperature <sup>9</sup> | +175°C           |
| Storage Temperature               | -65°C to +125°C  |

- Exceeding any one or combination of these limits may cause permanent damage to this device.
- MACOM does not recommend sustained operation near these survivability limits.
- Junction temperature directly effects device MTTF. Junction temperature should be kept as low as possible to maximize lifetime.

## Sample Board Layout



## Application Schematic



## Parts List

| Part                  | Value                  | Case Style |
|-----------------------|------------------------|------------|
| C1 - C6               | 0.01 $\mu$ F           | 0402       |
| C7 - C10              | 1 $\mu$ F              | 0402       |
| C11 - C13             | 10 $\mu$ F             | 0603       |
| R1 - R6               | 10 $\Omega$            | 0402       |
| L1 - L3 <sup>10</sup> | 600 $\Omega$ @ 100 MHz | 0603       |


10. L1 - L3 (chip ferrite bead) supplied from Murata, part number BLM18HE601SN1D.

## Sample Board Material Specifications

Top Layer: 1/2 oz Copper Cladding, 0.017 mm thickness  
Dielectric Layer: Rogers RO4003C 0.203 mm thickness  
Bottom Layer: 1/2 oz Copper Cladding, 0.017 mm thickness  
Finished overall thickness: 0.238 mm

## Recommended PCB Layout Detail:

RF input and output pre-matching circuit patterns are designed to compensate packaging effects. Transmission line dimensions apply to a PCB with 0.203 mm thick Rogers RO4003C laminate dielectric. Performance curves shown in this data sheet were measured with these circuit patterns.



## Biasing Conditions

Recommended biasing conditions are  $V_D = 6\text{ V}$ ,  $I_{DQ} = 900\text{ mA}$  (controlled with  $V_G$ ). The drain bias voltage range is 3 to 6 V, and the quiescent drain current biasing range is 600 to 1200 mA.

$V_G$  pins 10 and 11 are connected internally; choose either pin for layout convenience. Muting can be accomplished by setting the  $V_G$  to the pinched off voltage ( $V_G = -2\text{ V}$ ).

$V_D$  bias must be applied to  $V_{D1}$ ,  $V_{D2}$ ,  $V_{D3}$ , and  $V_{D4}$  pins.  $V_{D3}$  pins 27 and 28 are connected internally; choose either pin for layout convenience. Two  $V_{D4}$  pins 15 and 26 (not connected internally) are required for current symmetry.

## Operating the MAAP-011246

### Turn-on

1. Apply  $V_G$  (-1.5 V).
2. Apply  $V_D$  (6.0 V typical).
3. Set  $I_{DQ}$  by adjusting  $V_G$  more positive (typically -0.9 to -1.0 V for  $I_{DQ} = 900\text{ mA}$ ).
4. Apply  $RF_{IN}$  signal.

### Turn-off

1. Remove  $RF_{IN}$  signal.
2. Decrease  $V_G$  to -1.5 V.
3. Decrease  $V_D$  to 0 V.

## Power Amplifier, 2 W 27.5 - 31.5 GHz


Rev. V3

**Electrical Specifications with the Recommended PCB Layout and bias conditions:  
Freq. = 27.5 - 29.5 GHz,  $T_A = +25^\circ\text{C}$ ,  $V_D = 6\text{ V}$ ,  $Z_0 = 50\ \Omega$**


| Parameter              | Test Conditions                         | Units | Min. | Typ. | Max. |
|------------------------|---|-------|------|------|------|
| Gain                   | $P_{IN} = 0\text{ dBm}$                 | dB    | 19   | 27   | 30.5 |
| $P_{SAT}$              |   | dBm   | 31.5 | 33.5 | —    |
| IM3 Level              | $P_{OUT} = 27\text{ dBm / tone}$        | dBc   | —    | -20  | —    |
| Power Added Efficiency | $P_{SAT}$                               | %     | —    | 24   | —    |
| Input Return Loss      | $P_{IN} = -20\text{ dBm}$               | dB    | —    | 15   | —    |
| Output Return Loss     | $P_{IN} = -20\text{ dBm}$               | dB    | —    | 13   | —    |
| Quiescent Current      | $I_{DQ}$ (see bias conditions, page 4 ) | mA    | —    | 900  | —    |
| Current                | $P_{SAT}$                               | mA    | —    | 1600 | —    |

### Typical Performance Curves


**Gain vs. Frequency over Temperature**




**Gain vs. Frequency over Bias Voltage**



**Input Return Loss vs. Frequency over Temperature**




**Input Return Loss vs. Frequency over Bias Voltage**




## Typical Performance Curves over Temperature


**Output Return Loss vs. Frequency over Temperature**




**Output Return Loss vs. Frequency over Bias Voltage**




**P1dB Output Power vs. Frequency**




**PSAT Output Power vs. Frequency**



**OIP3 vs. Frequency ( $P_{OUT} = 27$  dBm/tone)**




**IM3 vs. Frequency ( $P_{OUT} = 27$  dBm/tone)**




## Typical Performance Curves over Bias Voltage


**$P_{1dB}$  Output Power vs. Frequency**




**$P_{SAT}$  Output Power vs. Frequency**



**OIP3 vs. Frequency ( $P_{OUT} = 27$  dBm/tone)**




**IM3 vs. Frequency ( $P_{OUT} = 27$  dBm/tone)**




## Typical Performance Curves over Frequency


**$P_{OUT}$  vs.  $P_{IN}$**




**OIP3 vs.  $P_{OUT}$  (dBm/tone)**




**PAE vs.  $P_{IN}$**



**IM3 Level vs.  $P_{OUT}$  (dBm/tone)**




**$I_{DS}$  vs.  $P_{IN}$**





**Lead-Free 5 mm AQFN 32-Lead<sup>†</sup>**



<sup>†</sup> Reference Application Note S2083 for lead-free solder reflow recommendations.  
 Meets JEDEC moisture sensitivity level 3 requirements.  
 Plating is NiPdAu.

MACOM Technology Solutions Inc. All rights reserved.

Information in this document is provided in connection with MACOM Technology Solutions Inc ("MACOM") products. These materials are provided by MACOM as a service to its customers and may be used for informational purposes only. Except as provided in MACOM's Terms and Conditions of Sale for such products or in any separate agreement related to this document, MACOM assumes no liability whatsoever. MACOM assumes no responsibility for errors or omissions in these materials. MACOM may make changes to specifications and product descriptions at any time, without notice. MACOM makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. MACOM FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. MACOM SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.