

## 5kW Single-Phase ATS/Metered PDU, 208/240V Outlets (16 C13, 2 C19 & 1 L6-30R) 2 L6-30P 10ft inputs, 2U Rack-Mount, TAA

MODEL NUMBER: PDUMH30HVAT



### Description

Tripp Lite Metered ATS / Auto Transfer Switch provides a redundant power option for single-corded network devices. Dual input cords support separate connection to PRIMARY and SECONDARY power sources. The ATS will normally maintain continuous output to all outlets as derived from the primary input cable. If the primary power source becomes unstable or fails altogether, the ATS will switch over to the secondary power source until the primary input is restored and stable. Highly reliable solid-state switching between primary and secondary inputs occurs in 1-5 milliseconds. ATS functionality is supported by any two compatible AC power sources, regardless of phase angle, to support a variety of advanced redundant power networking applications. Enables fault tolerant hot-swappable UPS protection when used with a single UPS and fully redundant UPS protection when each cord is connected to a separate UPS system. In a two-UPS environment, the primary input cable must be supported by a full time sine wave UPS with zero transfer time. Tripp Lite SmartOnline series is highly recommended for use as the primary UPS in a two-UPS application. ATS configurations utilizing separate mains circuits, backup generators and even separate utility power grid feeds are fully supported. On-board ATS processor constantly evaluates power quality on both input sources to prevent transfer to the secondary source when unavailable or of lower quality than the primary source. Front input LED's display primary or secondary power availability.

### Features

- 208/240V 30A Automatic Transfer Switch (ATS) / Metered PDU (Agency de-rated to 24A continuous)
- ATS features provide redundant power for critical network equipment with a single input power cord
- Digital display with selection button reports voltage, amperage and kilowatt loading information in four output segments (Segment 1: 8 C13 & 1 C19 outlets / Segment 2: 8 C13 & 1 C19 outlets / Segment 3: L6-30R outlet / Segment 4: total output of all outlets combined)
- 19 built-in outlets (16 C13, 2 C19, 1 L6-30R)

### Highlights

- Single phase 30A 208/240V Auto Transfer Switch / ATS Metered PDU with Solid State Switching
- Enables redundant-power configurations for single-corded network devices
- Separate primary & secondary inputs connect to any two compatible power sources
- 2U horizontal rackmount; 2 L6-30P inputs; 19 outlets (16 C13, 2 C19, 1 L6-30R)
- Front panel digital display with LED indicators reports output amps in 4 loading segments, plus total kW and input voltage
- Trade Agreements Act / TAA Compliant for GSA Schedule purchases

### Package Includes

- Auto Transfer Switch PDU
- Rackmount installation brackets
- Plug-lock cable retention sleeves
- Installable plug-retention shelves & cable ties



- Set of Plug-lock output power cable retention sleeves prevent accidental disconnection of connected devices
- Set of two 10 ft. / 3m NEMA L6-30P input cables support connection to separate PRIMARY and SECONDARY power sources
- ATS circuits normally maintain output sourced from the primary input cable; As primary input power fails or becomes unstable, the ATS will switch to maintain output as sourced from the secondary input cable until power on the primary input is restored and stable
- ATS configurations enable fault-tolerant, hot-swappable UPS protection when used with a single UPS and fully redundant UPS protection when each cord is connected to a separate UPS system (in a 2 UPS environment, the primary input must be connected to an online double conversion UPS similar to Tripp Lite SmartOnline series)
- Advanced ATS configurations utilizing separate mains circuits, backup generators and even separate out of phase utility power grid feeds are fully supported
- On-board ATS processor constantly evaluates power quality on both inputs to prevent transfer to the secondary source when unavailable or of lower quality than the primary source
- Super-fast switchover between primary and secondary power sources occurs in 1-5 milliseconds
- Front panel LEDs confirm power availability on both input lines
- Trade Agreements Act / TAA Compliant for GSA Schedule purchases

## Specifications

| OVERVIEW                       |  |
|--------------------------------|--|
| UPC Code                       | 037332159212   |
| PDU Type                       | Metered; Auto-Transfer Switch  |
| OUTPUT                         |  |
| Frequency Compatibility        | 50 / 60 Hz   |
| Output Capacity Details        | 5kW (208/240V), 4.8kW (200V) total capacity / 30A max (Agency de-rated to 24A), 24A max per L6-30R outlet; 20A max per breakered outlet bank; 16A max per C19 outlet; 12A max per C13 outlet     |
| Output Receptacles             | (16) C13; (2) C19; (1) L6-30R  |
| Output Nominal Voltage         | 200; 208; 240  |
| Overload Protection            | Includes two 20A output circuit breakers; Breaker 1 controls the upper row of 9 outlets (8 C13, 1 C19); Breaker 2 controls the lower row of outlets (8 C13, 1 C19); L6-30R outlet is unbreakered |
| INPUT                          |  |
| PDU Input Voltage              | 200; 208; 240  |
| Recommended Electrical Service | 30A 208V   |
| Maximum Input Amps             | 30   |



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
www.tripplite.com

|  |  |
|--|--|
| Maximum Input Amps Details                   | Agency de-rated to 24A continuous  |
| PDU Plug Type                                | (2) NEMA L6-30P  |
| Input Phase                                  | Single-Phase   |
| Input Cord Details                           | Set of two inputs connect to separate PRIMARY and SECONDARY power sources  |
| Input Cord Length (ft.)                      | 10   |
| Input Cord Length (m)                        | 3.05   |
| <b>USER INTERFACE, ALERTS &amp; CONTROLS</b> |  |
| Front Panel LCD Display                      | Digital display reports output amps in 4 separately metered loading segments (BANK 1: Outlets #1-9; BANK 2: Outlets #10-18; BANK 3: Outlet #19), whole-PDU output kW load level and input voltage on primary and secondary input lines |
| Front Panel LEDs                             | Front panel LEDs confirms amp / kilowatt / voltage reporting information   |
| Switches                                     | ENTER and MODE switches toggle the digital display to show output amps (Banks 1-4), total kW output and input voltage (primary, secondary)   |
| <b>PHYSICAL</b>                              |  |
| Minimum Required Rack Depth (inches)         | 16   |
| Minimum Required Rack Depth (cm)             | 40.64  |
| Shipping Dimensions (hwd / in.)              | 7.70 x 16.70 x 19.30   |
| Shipping Dimensions (hwd / cm)               | 19.56 x 42.42 x 49.02  |
| Shipping Weight (lbs.)                       | 20.30  |
| Shipping Weight (kg)                         | 9.21   |
| Unit Dimensions (hwd / in.)                  | 3.5 x 17.5 x 12.5  |
| Unit Dimensions (hwd / cm)                   | 8.8 x 44.4 x 31.7  |
| Unit Weight (lbs.)                           | 13.7   |
| Unit Weight (kg)                             | 6.21   |
| Material of Construction                     | Metal  |
| Form Factors Supported                       | 2U rackmount   |
| PDU Form Factor                              | Horizontal (2U)  |
| <b>ENVIRONMENTAL</b>                         |  |
| Storage Temperature Range                    | 5 to 122F (-15 to 50C)   |
| Relative Humidity                            | 5 to 95% (non-condensing)  |
| Operating Elevation (ft.)                    | 0-10,000   |
| Operating Elevation (m)                      | 0-3000   |
| <b>CERTIFICATIONS</b>                        |  |
| Certifications                               | Tested to UL 60950-1 (USA, Canada), Class A (Emissions), NOM (Mexico), RoHS Compliant, TAA Compliant   |



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
[www.tripplite.com](http://www.tripplite.com)

| WARRANTY                            |                         |
|-------------------------------------|-------------------------|
| Product Warranty Period (Worldwide) | 2-year limited warranty |

© 2019 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <https://www.tripplite.com/products/product-certification-agencies>