



Picture shows similar calibration kit

**Contents**

Device	Part number	Quantity	Calibration Option <sup>a</sup>
Open circuit plug	71S12L-000S3	1	FC
Open circuit jack	71K12L-000S3	1	FC
Short circuit plug	71S12S-000S3	1	FC
Short circuit jack	71K12S-000S3	1	FC
Calibration load plug	71S170-C10S3	1	FC
Calibration load jack	71K170-C10S3	1	FC
Calibration adaptor plug/plug	71S121-S20S3	1	FC
Calibration adaptor jack/jack	71K121-K20S3	1	FC

a. See "Declaration of calibration options" for explanation.

Dieses Dokument ist urheberrechtlich geschützt • This document is protected by copyright • Rosenberger Hochfrequenztechnik GmbH & Co. KG

RF\_35/05:10/6.1

**Documentation**

This kit is delivered with

- **USB-Stick**  
Standard Definitions as data files for Vector Network Analyzer Families PNA (Keysight/Agilent) and ZVA (Rohde&Schwarz). Calibration Certificate as PDF-file.
- **Standard Definitions Cards**  
Printed Standard Definitions that can be used on nearly all Vector Network Analyzers.
- **Kit Info Card**  
Handling precautions and information for installing Standard Definitions on a Vector Network Analyzer.
- **Calibration Certificate**  
Details see "Declaration of calibration options"
- **Operating Manual**

**Electrical specifications**

This specification covers electrical key values for the main calibration standards of the calibration kit. Specific datasheets are available for each component among the part number.

Calibration standard	Frequency	Parameter	Specification
<b>Opens<sup>b</sup></b> (plug and jack)	DC to ≤ 2 GHz > 2 GHz to ≤ 4 GHz	Error from Nominal Phase	≤ 3.0° ≤ 5.0°
<b>Shorts<sup>b</sup></b> (plug and jack)	DC to ≤ 2 GHz > 2 GHz to ≤ 4 GHz	Error from Nominal Phase	≤ 2.5° ≤ 4.0°
<b>Calibration loads</b> (plug and jack)	DC to ≤ 2 GHz > 2 GHz to ≤ 4 GHz	Return Loss	≥ 35 dB ≥ 30 dB
<b>Calibration adaptors</b> (plug/plug and jack/jack)	DC to ≤ 2 GHz > 2 GHz to ≤ 4 GHz	Return Loss	≥ 34 dB ≥ 30 dB

b. The specifications for opens and shorts are given as allowed deviation from nominal model as defined in calibration certificate included with your kit.

BNC  
75 Ω

Calibration Kit  
Industrial Version

**71CK010-170**

**Declaration of calibration options**

**Factory Calibration**

Standard delivery for this kit includes a Factory Calibration. The Calibration Certificate issued reports individual calibration results, **traceable to Rosenberger standards**, national / international standards are not available. Model based standard definitions of the calibration standards are reported in Agilent/Keysight, Rohde & Schwarz and Anritsu compatible VNA format.

**Accredited Calibration**

Not available.

*For further, more detailed information see application note AN001 on the Rosenberger homepage.*

**Calibration interval**

Recommendation 12 months

**Recommended accessories**

- Rosenberger Calibration Adaptor RPC-N 75 Ohm female to BNC 75 Ohm female P5K171-K2AS3
- Rosenberger Calibration Adaptor RPC-N 75 Ohm female to BNC 75 Ohm male P5K171-S2AS3
- Rosenberger Calibration Adaptor RPC-N 75 Ohm male to BNC 75 Ohm female P5S171-K2AS3
- Rosenberger Calibration Adaptor RPC-N 75 Ohm male to BNC 75 Ohm male P5S171-S2AS3
- Rosenberger Test Port Adaptor
- Rosenberger VNA Test cable kit and Microwave Cable Assemblies

*For further, more detailed information please visit our homepage [www.rosenberger.com](http://www.rosenberger.com).*

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Draft	Date	Approved	Date	Rev.	Engineering change number	Name	Date
Herbert Babinger	30.07.15	Martin Moder	16.09.15	b00	14-1492	Maik Knoll	16.09.15
Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany <a href="http://www.rosenberger.de">www.rosenberger.de</a>					Tel. : +49 8684 18-0 Fax : +49 8684 18-499 Email : <a href="mailto:info@rosenberger.de">info@rosenberger.de</a>		Page 3 / 3