


T493D476K010BH6410

T493 HRA, Tantalum, MnO2 Tantalum, HRA, 47 uF, 10%, 10 VDC, SMD, MnO2, Molded, High Reliability, B (0.1%/1000 Hrs), 800 mOhms, 7343, Height Max = 3.1mm



Click	horo	for	tho	3D	model
U.IICK	nere	TOL	The	.31)	model

Dimensions	
Footprint	7343
L	7.3mm +/-0.3mm
W	4.3mm +/-0.3mm
Н	2.8mm +/-0.3mm
Т	0.13mm REF
S	1.3mm +/-0.3mm
F	2.4mm +/-0.1mm
Α	3.8mm MIN
В	0.5mm +/-0.15mm
E	3.5mm REF
G	3.5mm REF
Р	0.5mm MIN
R	1mm REF
Χ	0.1mm +/-0.1mm

Packaging Specifications	
Packaging	T&R, 178mm
Packaging Quantity	500

General Information				
Series	T493 HRA			
Dielectric	MnO2 Tantalum			
Style	SMD Chip			
Description	SMD, MnO2, Molded, High Reliability			
Features	High Reliability			
RoHS	No			
Prop 65	▲ WARNING: Cancer and reproductive harm - http://www.p65warnings.ca.gov.			
SCIP Number	1dd2e1b8-26dd-4d52-927c-6f9d519011aa			
Termination	Solder Coated			
AEC-Q200	No			
Component Weight	412.33 mg			
Notes	P and R dimensions represents the minimum solderable area of the termination surface entirely below cutout (if one is present).			

Specifications	
Capacitance	47 uF
Capacitance Tolerance	10%
Voltage DC	10 VDC (85C), 6.7 VDC (125C)
Temperature Range	-55/+125°C
Rated Temperature	85°C
Dissipation Factor	6% 120Hz 25C
Failure Rate	B (0.1%/1000 Hrs)
Resistance	0.8 Ohms (100kHz 25C)
Ripple Current	433 mA (rms, 100kHz 25C)
Leakage Current	4.7 uA (5min 25°C)
Testing and Reliability	10 Cycles Surge Current Testing At -55C And +85C Before Weibull

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.