

# XCFR8.E333935 - Terminal Blocks Certified for Canada - Component

## Terminal Blocks Certified for Canada - Component

**ADAM TECH**  
 909 RAHWAY AVE  
 UNION, NJ 07083 United States

E333935

Cat. No.	Wire Range	Wire Type	TQ N-M	V	A	UG	CA
EBB [+1]	14 Sol	Cu	0.29	250	16	D	2(105)
	16 Str	Cu	0.29	250	16	D	2(105)
EBE [+1]	14 Sol	Cu	0.29	250	16	D	2(105), Note 2
	16 Str	Cu	0.29	250	16	D	2(105), Note 2
EBW [+1]	16-24 SOL/STR	Cu	0.19	300	10	B	2(115)
EBJ [+1]	14-22, Str/Sol	Cu	0.40	300	15	B	2(115), #12, Note 2
				Note A	Note A	D	
EBT [+2]	—	Cu	—	300	15	B	2(115), #12
				Note A	Note A	D	
EBH [+1]	16-28 Sol/Str	Cu	0.34	300	10	B, D	2(115), #8
EBV2 [+1]	12-22 Sol/Str	Cu	0.40	300	20	B	2(115), Note 7
	14-22 Sol/Str	Cu	0.40	300	15	B	2(115), Note 7
EBK [+1]	14-30, SOL/STR	Cu	0.23	300	10	B, D	2 (115), #45
EBR [+1]	—	—	—	300	10	B, D	2 (115), #45
EBP [+1], EBS [+1]	—	—	—	300	10	B, D	2(115), #8, #13
EBQ [+1]	—	—	—	300	20	B	2(115), #8, #13
					Note A	D	
EB-A [+1]	26-14	Cu	0.39	300	10	B, D	2 (115), #34
TDJ [+4]	20-6, STR/SOL	Cu	1.38	300	65	B	2 (115)
				300	Note A	D	

	20-6, STR/SOL	Cu	1.38	600	65	B, C	2 (115)
				600	Note A	D	
EB17 [+5]	12-24 Sol/Str	Cu	0.41	300	16	B	2(105), 4
EB15 [+5]	14-26 Sol/Str	Cu	0.25	300	8	B, D	2(105)
EBAG [+5]	12-22 Sol/Str	Cu	0.4	600	16	B	2(105)
					Note A	D	
EB105 [+5]	12-22 Sol/Str	Cu	0.4	600	16	B	2(105)
					Note A	D	
EBAG [+5]	12-22 Sol/Str	Cu	0.4	300	16	B	2(105)
					Note A	D	
EBAD [+5]	12-22 Sol/Str	Cu	0.4	600	16	B	2(105)
					Note A	D	
EBA [+5]	14-22 Sol/Str	Cu	0.25	250	16	B	2(105)
					Note A	D	
EBD [+5]	14-22 Sol/Str	Cu	0.25	250	16	B	2(105)
					Note A	D	
EBEA [+5]	14-22 Sol/Str	Cu	0.25	250	16	B	2(105)
					Note A	D	
EB169 [+5]	14-22 Sol/Str	Cu	0.25	250	16	B	2(105)
					Note A	D	
EBB [+5]	14-22 Sol/Str	Cu	0.25	250	16	B	2(105)
					Note A	D	
EBC [+5]	18-24 Sol/Str	Cu	0.19	300	10	B	2(105)
					Note A	D	
EBF [+5]	18-24 Sol/Str	Cu	0.19	300	10	B	2(105)
					Note A	D	
EB166 [+5]	14-22 Sol/Str	Cu	0.45	300	10	B,D <sup>A</sup>	2(105)
EB106 [+5]	14-26 Sol/Str	Cu	0.39	600	12	B,D <sup>A</sup>	2(105)
EB21 [+5]	14-26 Sol/Str	Cu	0.39	600	12	B,D <sup>A</sup>	2(105)
EB18 [+5]	14-26 Sol/Str	Cu	0.39	600	12	B,D <sup>A</sup>	2(105)

EB147 [+5]	12-26 Sol/Str	Cu	0.41	300	20	B,D <sup>A</sup>	2(105)
------------	---------------	----	------	-----	----	------------------	--------

EBI [+5]	12-26 Sol/Str	Cu	0.41	300	20	B,D <sup>A</sup>	2(105)
EB144 [+5]	12-26 Str/Sol	Cu	0.41	300	20	B	2(105)
					Note A	D	
EB38 [+5]	12-26 Str/Sol	Cu	0.41	300	20	B	2(105)
					Note A	D	
TBP [+8]	14-22 Sol/Str	Cu	0.51	300	15	B,D <sup>A</sup>	2(105),3(M3)
TBD [+8]	12-22 Sol/Str	Cu	0.51	150	20	C	2(105), 3(M3)
					Note A	D	
TBC [+8]	12-22 Sol/Str	Cu	0.51	300	20	B,D <sup>A</sup>	2(105), 3(M3)
TBG [+8]	12-22 Sol/Str	Cu	1.19	300	20	B,D	2 (105)
TBY [+8]	12-22 Sol/Str	Cu	1.7	300	20	B,D	2 (105)
EB71 [+5]	12-28 Sol/Str	Cu	-	300	15	B,D <sup>A</sup>	2(105)
EB104 [+5]	12-28 Sol/Str	Cu	-	300	15	B,D <sup>A</sup>	2(105)
EB63 [+5]	12-28 Sol/Str	Cu	-	300	15	B,D <sup>A</sup>	2(105)
EB69 [+5]	12-28 Sol/ Str	Cu	-	300	10	B,D <sup>A</sup>	2(105)
EB70 [+5]	12-28 Sol/ Str	Cu	-	300	10	B,D <sup>A</sup>	2(105)
EB59 [+5]	18-22 Sol/Str	Cu	-	300	5	B,D <sup>A</sup>	2(105)
EB15A [+6]	14-26 Sol/Str	Cu	0.25	300	8	B, D	2(105)
EB174A [+6]	14-22 Sol/Str	Cu	0.25	250	16	B	2(105)
EB17A [+6]	12-24 Sol/Str	Cu	0.41	300	16	B	2(105), 4
EB17B [+6]	12-24 Sol/Str	Cu	0.41	300	16	B	2(105), 4
EBAA [+6]	14-22 Sol/Str	Cu	0.25	250	16	B	2(105)
EBAD [+6]	12-22 Sol/Str	Cu	0.40	300	16	B	2(105), 4
EBAD-A [+6]	12-22 Sol/Str	Cu	0.40	300	16	B	2(105), 4
EBAFA [+6]	12-22 Sol/Str	Cu	0.40	300	16	B	2(105), 4
EBAG [+6]	12-22 Sol/Str	Cu	0.40	600	16	B	2(105), 4
EBBA [+6]	14-22 Sol/Str	Cu	0.19	250	16	B	2(105)
EBCA [+6]	18-24 Sol/Str	Cu	0.25	300	10	B	2(105)
EBDA [+6]	14-22 Sol/Str	Cu	0.25	250	16	B	2(105)
EBEA [+6]	14-22 Sol/Str	Cu	0.25	250	16	B	2(105)
EBEAA [+6]	14-22 Sol/Str	Cu	0.25	250	16	B	2(105)
TDHA [+3]	10-20 Sol/Str	Cu	0.5- 0.52	300	30	B,D	2(105),4

REB [+14]	16-28 Sol/Str	Cu	0.22	300	10	B,C	2(105),4
EB125A [+6]	12-26 Str/Sol	Cu	0.5	300	20	B	2(105), 4
EB144A [+6]	12-26 Str/Sol	Cu	0.5	300	20	B	2(105), 4
EB147A [+6]	12-26 Str/Sol	Cu	0.5	300	20	B	2(105), 4
EB166A [+11]	14-22 Sol/Str	Cu	0.45	300	10	B,D <sup>A</sup>	2(105),4
EB178A [+6]	12-26 Str/Sol	Cu	0.5	300	20	B	2(105), 4
EB21A [+6]	14-26 Sol/Str	Cu	0.39	300	12	B,D <sup>A</sup>	2(105), 4
EB21-A [+6]	14-26 Sol/Str	Cu	0.39	300	12	B,D <sup>A</sup>	2(105), 4
EB38A [+6]	12-26 Str/Sol	Cu	0.5	300	20	B	2(105), 4
TBCA [+3]	12-22 Sol/Str	Cu	0.51	150	20	C	2(105), 3(M3)
				300	20	B	
TBGA [+3]	12-22 Sol/Str	Cu	1.19	300	20	B,D	2(105)
TBP [+3]	14-22 Sol/Str	Cu	0.51	150	15	B,C	2(105),3(M3)
EB104A [+6]	12-28 Sol/Str	Cu	—	300	15	B,D <sup>A</sup>	2(105),4
EB59 [+6]	18-22 Sol/Str	Cu	—	300	5	B,D <sup>A</sup>	2(105),4
EB59A [+6]	18-22 Sol/Str	Cu	—	300	5	B,D <sup>A</sup>	2(105),4
EB63A [+6]	12-28 Sol/Str	Cu	—	300	15	B,D <sup>A</sup>	2(105),4
EB69A [+6]	12-28 Sol/ Str	Cu	—	300	10	B,D <sup>A</sup>	2(105),4
EB71A [+6]	12-28 Sol/Str	Cu	—	300	15	B,D <sup>A</sup>	2(105),4
<b>Plug-in blocks</b>							
EB52 [+5]	28-12, Str/Sol	Cu	0.51	300	15	B,D <sup>A</sup>	2(105),#1
EB118 [+5]	28-12, Str/Sol	Cu	0.51	300	15	B,D <sup>A</sup>	2(105),#1
EBH [+6]	28-12, Str/Sol	Cu	0.51	300	15	B,D <sup>A</sup>	2(105),#1
EB44 [+6]	28-12, Str/Sol	Cu	0.51	300	15	B,D <sup>A</sup>	2(105),#1
EB9 [+6]	28-12, Str/Sol	Cu	0.51	300	15	B,D <sup>A</sup>	2(105),#1
EB47 [+6]	28-12, Str/Sol	Cu	0.51	300	15	B,D <sup>A</sup>	2(105),#1
EB124 [+5]	16-28, Str/Sol	Cu	0.4	300	10	B	2 (105), #1
					Note A	D	
EBT [+7]	16-28, Str/Sol	Cu	0.4	300	10	B	2 (105), #1
					Note A	D	
EBJ [+5]	16-28, Str/Sol	Cu	0.4	300	10	B	2 (105), #1

					Note A	D	
EB6 [+10]	28-12, Str/Sol	Cu	0.51	300	15	B,D <sup>A</sup>	2(105),#1
EB180A [+6]	28-12, Str/Sol	Cu	0.51	300	15	B,D <sup>A</sup>	2(105)
EB47A [+11]	28-12, Str/Sol	Cu	0.51	300	15	B,D <sup>A</sup>	2(105),#1
EB6A [+6]	28-12, Str/Sol	Cu	0.51	300	15	B,D <sup>A</sup>	2(105),#1
EB9A [+6]	28-12, Str/Sol	Cu	0.51	300	15	B,D <sup>A</sup>	2(105),#1
EBHA [+6]	28-12, Str/Sol	Cu	0.51	600	15	B	2(105),#1
EBJA [+6]	16-28, Str/Sol	Cu	0.4	300	10	B	2 (105), #1

**Headers**

EBQ [+6]	—	—	—	300	15	B,D <sup>A</sup>	2(105),#1
EB48 [+6]	—	—	—	300	15	B,D <sup>A</sup>	2(105),#1
EBQ2 [+6]	—	—	—	300	15	B,D <sup>A</sup>	2(105),#1
EBP [+6]	—	—	—	300	15	B,D <sup>A</sup>	2(105),#1
EBP2 [+6]	—	—	—	300	15	B,D <sup>A</sup>	2(105),#1
EB41 [+6]	—	—	—	300	15	B,D <sup>A</sup>	2(105)
EB41A [+6]	—	—	—	300	15	B,D <sup>A</sup>	2(105), #3
EB52A [+6]	28-12, Str/Sol	Cu	0.51	300	15	B,D <sup>A</sup>	2(105),4, #3
EB86A [+6]	28-12, Str/Sol	Cu	0.51	300	15	B,D <sup>A</sup>	2(105),4, #3
EBP2A [+6]	—	—	—	300	15	B,D <sup>A</sup>	2(105)
EBPA [+6]	—	—	—	300	15	B,D <sup>A</sup>	2(105), #3
EBQ2A [+6]	—	—	—	300	15	B,D <sup>A</sup>	2(105)
EBQA [+6]	—	—	—	300	15	B,D <sup>A</sup>	2(105), #3
EBTA [+6]	—	—	—	300	10	B	2 (105), #3

**Terminal blocks**

EBK [+6]	16-28, Str/Sol	Cu	0.2	300	8	B	2(105),#1
					Note A	D	
EB12 [+6]	16-28, Str/Sol	Cu	0.2	300	8	B	2(105),#1
					Note A	D	
EB5 [+6]	16-28, Str/Sol	Cu	0.2	300	8	B	2(105),#1

					Note A	D	

EBS [+6]	-	-	-	300	8	B	2(105),#1
					Note A	D	
EB8 [+6]	-	-	-	300	8	B	2(105), #1
					Note A	D	
EBR [+6]	-	-	-	300	8	B	2(105), #1
					Note A	D	
EB3 [+6]	-	-	-	300	8	B	2(105),#1
					Note A	D	
EB28 [+5]	14-30, Str/Sol	Cu	0.4	300	15	B	2(105)
					Note A	D	
EB27 [+5]	14-30, Str/Sol	Cu	0.4	300	15	B	2(105)
					Note A	D	
EB22 [+5]	14-30, Str/Sol	Cu	0.4	300	15	B	2(105)
					Note A	D	
EB23 [+5]	14-30, Str/Sol	Cu	0.4	300	15	B	2(105)
					Note A	D	
EBW [+5]	16-28, Str/Sol	Cu	0.2	300	10	B	2(105)
					Note A	D	
EB25 [+5]	16-28, Str/Sol	Cu	0.2	300	10	B	2(105)
					Note A	D	
EB31 [+5]	16-28, Str/Sol	Cu	0.2	300	10	B	2(105)
					Note A	D	
EB20 [+5]	14-30, Str/Sol	Cu	0.4	600	15	B	2(105)
					Note A	D	
EBV [+5]	14-30, Str/Sol	Cu	0.4	300	15	B	2(105)
					Note A	D	
EBV2 [+5]	14-30, Str/Sol	Cu	0.4	300	15	B	2(105)
					Note A	D	
EB14 [+5]	12-26, Str/Sol	Cu	0.4	300	20	B	2 (105)
					Note A	D	

EB161 [+5]	6-20, Str/Sol	Cu	1.4	300	52	B, C	2 (105)
------------	---------------	----	-----	-----	----	------	---------

				600	Note A	D	
EB32 [+5]	6-20, Str/Sol	Cu	1.4	300	52	B, C	2 (105)
				600	Note A	D	
EB-TW [+7]	14-24, Str/Sol	Cu	-	300	10	B	2 (105)
					Note A	D	
EB-FW [+5]	14-24, Str/Sol	Cu	-	300	10	B	2 (105)
					Note A	D	
TBA [+8]	16-22, Str/Sol	Cu	0.4	300	10	B	2 (105)
					Note A	D	
EB13 [+5]	14-26, Str/Sol	Cu	0.4	300	15	B, C	2 (105)
				600	Note A	D	
EB145 [+5]	12-26, Str/Sol	Cu	0.25	300	15	B	2 (105)
					Note A	D	
TBB [+8]	16-22, Str/Sol	Cu	0.4	300	10	B	2 (105)
					Note A	D	
TBE [+8]	12-22, Str/Sol	Cu	0.5	300	20	B, C	2 (105)
					Note A	D	
TBR [+8]	12-22, Str/Sol	Cu	0.5	300	20	B	2 (105)
					Note A	D	
TBF [+8]	12-22, Str/Sol	Cu	1.2	300	20	B	2 (105)
					Note A	D	
EB4 [+5]	10-26, Str/Sol	Cu	0.5	300	30	B	2 (105)
					Note A	D	
TBN [+8]	12-22, Str/Sol	Cu	1.2	300	20	B, C	2 (105)
					Note A	D	
TBM [+8]	10-22, Str/Sol	Cu	1.2	300	30	B, C	2 (105)
					Note A	D	
EB119 [+5]	10-26, Str/Sol	Cu	0.5	300	30	B	2 (105)
					Note A	D	
TBW [+8]	10-18, Str/Sol	Cu	1.25	600	30	B, C	2 (105)

					Note A	D	
EB32 [+5]				300	15	B	2 (105)

EB88 [+6]	—	—	—	300	15	B	2(125)
					Note A	D	
EBE [+5]	26-18, str/sol	Cu	—	150	4	B	2(125)
EB49 [+5]	—	—	—	300	8	B	2(105)
					Note A	D	
EB40 [+5]	—	—	—	300	8	B	2(105)
					Note A	D	
EB50 [+6]	—	—	—	300	8	B	2(105)
					Note A	D	
EB6 [+6]	28-16, str/sol	Cu	0.2	300	8	B	2(105)
					Note A	D	
EB84 [+5]	28-16, str/sol	Cu	—	300	8	B	2(105)
					Note A	D	
EB160 [+5]	28-16, str/sol	Cu	—	300	8	B	2(105)
					Note A	D	
EB2 [+6]	28-16, str/sol	Cu	—	300	8	B	2(105)
					Note A	D	
EB90 [+5]	24-16, str/sol	Cu	—	300	8	B	2(125)
					Note A	D	
EB96 [+6]	28-16, str/sol	Cu	0.2	300	8	B	2(105)
					Note A	D	
EB86 [+6]	28-16, str/sol	Cu	0.2	300	8	B	2(105)
					Note A	D	
EB168 [+5]	—	—	—	300	8	B	2(65)
EB102 [+6]	—	—	—	300	8	B	2(65)
EB46 [+6]	26-16, str/sol	Cu	—	300	10	B	2(105)
EB157 [+5]	—	—	—	300	15	B	2(105)
					Note A	D	
EB51 [+6]	-	-	-	300	15	B	2(105)
					Note A	D	

EBG [+5]	28-14, str/sol	Cu	0.4	300	15	B	2(105)
EB161 [+5]	28-14, str/sol	Cu	0.4	300	15	B	2(105)



EB16 [+5]	28-14, str/sol	Cu	0.4	300	15	B	2(105)
EB96 [+5]	28-14, str/sol	Cu	0.4	300	12	B	2(105)
					Note A	D	
EB103 / 128 [+5]	28-14, str/sol	Cu	0.4	300	12	B	2(105)
					Note A	D	
EB107 [+5]	28-14, str/sol	Cu	0.4	300	12	B	2(105)
					Note A	D	
EB114 [+5]	28-14, str/sol	Cu	0.4	300	12	B	2(105)
					Note A	D	
EB151 [+5]	20-6, str/sol	Cu	1.2	600	65	B, C	2(105)
					Note A	D	
EB33 [+5]	20-6, str/sol	Cu	1.2	600	65	B, C	2(105)
					Note A	D	
EBB2 [+5]	26-14, str/sol	Cu	0.4	300	12	B	2(105)
					Note A	D	
EB153 [+5]	26-10, str/sol	Cu	1.2	300	30	B	2(120)
					Note A	D	
EB142 [+5]	24-16, str/sol	Cu	-	300	10	B	2(130), 4
					Note A	D	
EB58 [+5]	22-18, str/sol	Cu	-	300	5	B	2(120)
					Note A	D	
EB62 [+5]	20-16, str/sol	Cu	-	300	10	B	2(120)
					Note A	D	
EB79 [+5]	20-12, str/sol	Cu	-	300	12	B,C	2(120)
					Note A	D	
EB42 [+5]	24-8, Str/Sol	Cu	0.5	300	41	B	2(115)
					Note A	D	
EB43 [+5]	-	Cu		300	41	B, C	2(115)
					Note A	D	
EB152 [+5]	26-12, str/sol	Cu	0.5	300	20	B	2(115)

					Note A	D	
EB151 [+5]	20-6, str/sol	Cu	1.2	600	65	B, C	2(105)

IDA [+8]	22-12, str/sol	Cu	0.8	300	20	B, C	2(120)
					Note A	D	
TDB [+8]	22-12, str/sol	Cu	0.8	300	25	B, C	2(120)
					Note A	D	
TDC [+8]	22-10, str/sol	Cu	1.2	600	30	B	2(120)
					Note A	D	
EB159 [+5]	26-18, str/sol	Cu	0.1	150	7	B	2(115)
EB10 [+5]	26-14, str/sol	Cu	0.4	300	15	B	2(115)
					Note A	D	
EB11 [+5]	26-14, str/sol	Cu	0.4	300	15	B	2(115)
					Note A	D	
TBU [+8]	14-6, str/sol	Cu	2.82	600	65	B,C	2(130), 5
					Note A	D	
EB60 [+5]	22-16, str/sol	Cu	-	300	10	B	2(125)
					Note A	D	
EB167 [+6]	18-4, str/sol	Cu	-	600	66	B,C	2(125)
					Note A	D	
EB130 [+6]	18-4, str/sol	Cu	-	600	66	B,C	2(125)
					Note A	D	
EB171 [+6]	18-4, str/sol	Cu	-	600	51	B,C	2(125)
					Note A	D	
EB172 [+6]	20-16, str/sol	Cu	-	300	10	B	2(120)
					Note A	D	
EB175 [+6]	10-26, Str/Sol	Cu	0.5	300	30	B	2 (105)
					Note A	D	
TDP[+9]	22-12 Str/Sol	Cu	0.8	300	20	B	2(130)
EB163 [+11]	24-12, str/sol	Cu	—	300	20	B	2(125)
EB20 [+6]	14-30, Str/Sol	Cu	0.4	300	15	B	2(105),4
EB22A [+6]	14-30, Str/Sol	Cu	0.4	300	15	B	2(105),4
EB25A [+6]	16-28, Str/Sol	Cu	0.2	300	10	B	2(105),4
EB27A [+6]	14-30, Str/Sol	Cu	0.4	300	15	B	2(105),4
EB28A [+6]	14-30, Str/Sol	Cu	0.4	300	15	B	2(105),4

EB48A [+6]	—	—	—	300	8	B	2(105), #3
EB5A [+6]	16-28, Str/Sol	Cu	0.2	300	8	B	2(105),4, #3
EBK [+6]	16-28, Str/Sol	Cu	0.2	300	8	B	2(105),4, #3
EBRA [+6]	—	—	—	300	8	B	2(105), #3
EBRAH [+6]	—	—	—	300	8	B	2(110), #3
EBSA [+6]	—	—	—	300	8	B	2(105), #3
EBV2A [+6]	14-30, Str/Sol	Cu	0.4	300	15	B	2(105),4
EBVA [+6]	14-30, Str/Sol	Cu	0.4	300	15	B	2(105),4
EBWA [+6]	16-28, Str/Sol	Cu	0.2	300	10	B	2(105),4
EB145A [+6]	12-26, Str/Sol	Cu	0.25	300	15	B	2 (105), 4
EB147DA [+6]	10-24, Str/Sol	Cu	0.5	300	30	B	2 (105), 4
EB14A [+6]	12-26, Str/Sol	Cu	0.4	300	20	B	2 (105), 4
EB161A [+11]	6-20, Str/Sol	Cu	1.4	300	52	B, C	2 (105), 4
EB175A [+6]	10-26, Str/Sol	Cu	0.5	300	30	B	2 (105), 4
EB4A [+6]	10-26, Str/Sol	Cu	0.5	300	30	B	2 (105), 4
EB109A [+6]	10-26, Str/Sol	Cu	0.5	300	30	B, C	2 (105), 4
EB7A [+6]	12-26, Str/Sol	Cu	0.4	300	20	B	2 (105), 4
EB-FWA [+6]	14-24, Str/Sol	Cu	—	300	10	B	2 (105), 4
TBBA [+3]	16-22, Str/Sol	Cu	0.4	300	10	B	2 (105), 4
TBEA [+3]	12-22, Str/Sol	Cu	0.5	300	20	B, C	2 (105), 4
TBFA [+3]	12-22, Str/Sol	Cu	1.2	300	20	B	2 (105), 4
TBFB [+3]	12-22, Str/Sol	Cu	1.2	300	20	B	2 (105), 4
TBNA [+3]	12-22, Str/Sol	Cu	1.2	300	20	B, C	2 (105), 4
TBRB [+3]	12-22, Str/Sol	Cu	0.5	300	20	B	2 (105), 4
TBWA [+3]	10-18, Str/Sol	Cu	1.25	600	40	B, C	2 (105)
					Note A	D	
	10-18, Str/Sol	Cu	1.25	600	30	B, C	2 (105), 4
EB102A [+6]	—	—	—	300	8	B	2(65)
EB157A [+6]	—	—	—	300	15	B	2(105)
EB168A [+6]	—	—	—	300	8	B	2(65)
EB179A [+6]	24-16, str/sol	Cu	—	300	8	B	2(125),4

EB2A [+6]	28-16, str/sol	Cu	—	300	8	B	2(105), 4
EB2A [+6]				150	8	B	2(105)

EB3A [+0]	—	—	—	150	5	B	2(105)
EB46SB [+6]	26-18, str/sol	Cu	—	150	5	B	2(125), 4
EB49A [+6]	—	—	—	300	8	B	2(105)
EB50A [+6]	—	—	—	300	15	B	2(105)
EB51A [+6]	—	—	—	300	15	B	2(105)
EB65A [+6]	28-12, str/sol	Cu	—	300	15	B	2(125), 4
EB85A [+6]	28-12, str/sol	Cu	—	300	10	B	2(105), 4
EB88A [+6]	—	—	—	300	15	B	2(125)
EB89A [+6]	12-28 Sol/Str	Cu	—	300	15	B	2(125), 4
EB90A [+6]	24-16, str/sol	Cu	—	300	8	B	2(125),4
EB90DA [+6]	24-16, str/sol	Cu	—	300	8	B	2(125),4
EB96A [+6]	28-14, str/sol	Cu	0.4	300	12	B	2(105), 4
EBGA [+6]	28-14, str/sol	Cu	0.4	300	12	B	2(105), 4
EB-TWA [+6]	26-18, str/sol	Cu	—	150	4	B	2(125), 4
TDGA [+3]	20-12, str/sol	Cu	0.4	600	20	B,C	2(105), 4
TDJA [+3]	20-6, str/sol	Cu	1.2	600	65	B,C	2(125), 4
TDKA [+3]	22-14, str/sol	Cu	0.4	300	15	B,C	2(105), 4
EB151A [+6]	20-6, str/sol	Cu	1.2	600	65	B, C	2(105), 4
EBYA [+6]	20-6, str/sol	Cu	1.2	600	65	B, C	2(105), 4
EBYAB [+6]	20-6, str/sol	Cu	1.8	600	65	B, C	2(105), 4
EB142A [+6]	24-16, str/sol	Cu		300	10	B	2(130), 4
EB152A [+6]	26-12, str/sol	Cu	0.5	300	20	B	2(115), 4
EB153A [+6]	26-10, str/sol	Cu	1.2	300	30	B	2(120), 4
EB159 [+6]	26-18, str/sol	Cu	0.1	150	7	B	2(115), 4
EB185A [+6]	28-14, str/sol	Cu		300	10	B	2(120), 4
EB33A [+6]	20-2, str/sol	Cu	4.5	600	115	B, C	2(115), 4
EB42A [+6]	28-10, str/sol	Cu	0.5	300	30	B	2(115), 4
EB43A [+6]	—	Cu		300	30	B, C	2(115)
EB58A [+11]	22-18, str/sol	Cu		300	5	B	2(120), 4
EB62A [+6]	20-16, str/sol	Cu		300	10	B	2(120), 4
EB79A [+6]	20-12, str/sol	Cu		300	12	B, C	2(120), 4

EB81A [+6]	24-8, Str/Sol	Cu	0.5	300	41	B	2(115), 4
EB95A [+6]	26-14, str/sol	Cu	0.4	300	15	B	2(115), 4

EBAEA [+6]	Z6-14, str/sol	Cu	0.4	300	15	B	2(115), 4
TDA [+3]	22-12, str/sol	Cu	0.8	300	20	B, C	2(120), 4
TDB [+3]	22-12, str/sol	Cu	0.8	300	25	B, C	2(120), 4
EB130A [+6]	24-8, str/sol	Cu	-	600	40	B,C	2(125),4
EB163A [+6]	24-16, str/sol	Cu	-	300	10	B	2(125),4
EB167A [+6]	18-4, str/sol	Cu	-	600	66	B,C	2(125),4
EB171A [+6]	18-4, str/sol	Cu	-	600	51	B,C	2(125),4
EB181A [+6]	-	Cu	-	150	4	B	2(120)
EB187A [+6]	24-16, str/sol	Cu	-	300	12	B	2(125),4
EB60A [+6]	22-16, str/sol	Cu	-	300	10	B	2(125),4
EBJSA [+6]	28-16, str/sol	Cu	0.2	300	8	B	2(115),4
TBU [+3]	8-2, str	Cu	2.94	600	115	B,C	2(130), 5
TBUA [+3]	22-10, str/sol	Cu	1.76	300	30	B,C	2(130),4
REB [+13]	28-16 Str/Sol	Cu	—	300	10	B	2(120),4
REB [+15]	26-14 Str/Sol	Cu	—	300	15	B,C	2(115),4
EB171SA [+6]	24-10 Str/Sol	Cu	—	600	27	B,C	2(125),4
EB173A [+6]	26-16 Str/Sol	Cu	—	300	10	B	2(125),4
EB74A [+6]	24-10 Str/Sol	Cu	—	300	30	B	2(120),4
EB78A [+6]	20-16 Str/Sol	Cu	—	300	8	B	2(120),4
EB137A [+6]	30-12 Str/Sol	Cu	0.5	300	18	B	2(120), 4
EB138A [+6]	-	-	-	300	18	B	2(120)
REB [+12]	26-14, Str/Sol	Cu	-	300	15	B, C	2(115), 4
EB146 [+6]	-	-	-	150	7	B	2(65)
EB188A [+6]	28-18, Str/Sol	Cu	-	150	7	B	2(120), 4
EB90DB [+6]	26-16, Str/Sol	Cu	-	300	9.5	B	2(65), 4
EB46A [+6]	—	Cu		300	55	B, C	2(120)
EB46SA [+6]	26-14, str/sol	Cu	—	300	10	B	2(105) , 4
EB119A [+6]	10-26, Str/Sol	Cu	4.4	300	30	B, C	2 (105), 4

[+1] - Followed by 02 thru 24, followed by A thru V, maybe followed by C or E, maybe followed by BK or GY, maybe followed by letter A w/ 5 numerical digits.

[+2] - Followed by 02 thru 24, followed by A thru V, maybe followed by numerical digits, maybe followed by letter A w/ 5 numerical digits.

[+3] - Followed by alphanumeric digits, followed by 02 thru 24, followed by A thru V, maybe followed by C or E, maybe followed by BK or GY, maybe followed by letter A w/ 5 numerical digits.

[+4] - Followed by 01 through 12.

[+5] - Model may be f/b A, f/b 01 thru 99, f/b A thru Z, may be f/b up to four alpha digits, may be f/b HT, PP, T/R may be f/b letter A w/ 5 numerical digits or blank.

[+6] - Model may be f/b A, f/b 01 thru 99, f/b A thru Z, maybe f/b C or E, may be f/b up to four alpha digits, may be f/b HT, PP, T/R may be f/b letter A w/ 5 numerical digits or blank.

[+7] - Model may be f/b A, f/b 01 thru 99, f/b A thru Z, may be f/b up to four alpha digits, may be f/b numerical digits, may be f/b HT, PP, T/R, may be f/b letter A w/ 5 numerical digit.

[+8] - Model may be f/b A, f/b 01 thru 99, f/b 2 numerical digits, f/b B or M, may be f/b alpha numerical digits, may be f/b HT or T/R, may be f/b letter A w/ 5 numerical digits or blank.

[+9] - Model may be f/b A, f/b 01 thru 99, f/b 2 numerical digits, f/b B or M, maybe f/b alpha numerical digits, maybe f/b HT or T/R, maybe f/b letter A w/ 5 numerical digits or blank

[+10] - Model may be f/b A, f/b 01 thru 99, f/b C or D, maybe f/b C or E, maybe f/b up to four alpha digits, maybe f/b HT, PP, T/R maybe f/b letter A w/ 5 numerical digits or blank.

[+11] - Model may be f/b A, f/b 01 thru 99, f/b C, maybe f/b 90 or 180, maybe f/b HT, PP, T/R maybe f/b letter A w/ 5 numerical digits or blank.

[+12] – Followed by two to three alphanumeric digits or blank, followed by two to four alphanumeric digits or blank. followed by A, B, C... Z or blank.

[+13] – Followed by 01 thru 99, followed by three alphanumeric digits or blank, followed by two to four alphanumeric digits or blank, followed by A, B, C... Z or blank.

[+14] – Followed by 0000 thru 9999 or blank, followed by three alphanumeric digits or blank, followed by two to four alphanumeric digits or blank. followed by A, B, C... Z or blank.

[+15] – Followed by two to four alphanumeric digits or blank. followed by A, B, C... Z or blank.

Note: A - These limited ratings are applicable to a terminal block for use in or with industrial control equipment whereby the load on any single circuit of the terminal block does not exceed 15 A at 51-150 V, or 10 A at 151-300 V, or the maximum ampere rating, whichever is less.

Note: 2 - The terminal blocks are constructed end to end stackable design, which may be assembled 4 thru 24 poles. The suitability of the assembly shall be determined in the end-use investigation.

Note: 7 - The terminal blocks are constructed end to end stackable design, which may be assembled 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48 poles. The suitability of the assembly shall be determined in the end-use investigation.

#1 The terminal blocks as tabulated below consist of two halves with plug consisting of the Pressure Wire Connector Type and header consisting of the Soldering Post Type terminals. These devices have not been evaluated to make or break the flow of current. These devices are not evaluated for use with any other mating connectors.

#8 Model EBH and EBP, EBQ, and EBS Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#12 Model EBJ and EBT with letter 2 or 3 for fifth digit of catalog number; Model EBJ and EBT with letter 4 or 5 for fifth digit of catalog number; Model EBT with letter 4 or 5 for fifth digit of catalog number; Model EBJ and EBT with letter 0 or 1 for fifth digit of catalog number; Model EBT with letter 0 or 1 for fifth digit of catalog number are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#13 Model EBP, EBQ, and EBS Series; Model EBP, EBQ, and EBS Series; Model EBP, EBQ, and EBS Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#34 Model EBT Series and Model EBT Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#45 Model EBK Series and EBR Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

Plug-in Block Series No.	Mating Header Series No.

Marking: Company name and the Recognized Component Mark for Canada



on the product. Catalog designation, maximum voltage,

wire range and ampere rating appear on the device or in or on the carton.

Last Updated on 2022-10-26

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL Solutions' Follow - Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL Solutions' Follow - Up Service. Always look for the Mark on the product.

UL Solutions permits the reproduction of the material contained in Product iQ subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from Product iQ with permission from UL Solutions" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "©2022 UL LLC."