

PLEASE CHECK WWW.MOLEX.COM FOR LATEST PART INFORMATION

Part Number: [0732980090](#)
Status: **Active**
Overview: BMA Blind-Mate RF Connectors
Description: 50 Ohms, BMA Jack, 4 Hole Flange Mount

Documents:

3D Model	3D Model (PDF)
Drawing (PDF)	RoHS Certificate of Compliance (PDF)

General

Product Family	RF/Coax Connectors
Series	73298
Comments	VOLTAGE 250 Vrms at Sea Level (Cable group II MIL-PRF-31031 Appendix A) 335 Vrms at Sea Level (Cable group VI MIL-PRF-31031 Appendix A)
Overview	<u>BMA Blind-Mate RF Connectors</u>
Product Name	BMA
Style	Cable
Type	Subminiature
UPC	884982908734
Wire/Cable Type	N/A

Physical

Cable Attachment	Crimp, Solder
Gender	Jack
Keying to Mating Part	None
Orientation	Straight
PCB Mounting	N/A
Packaging Type	Tray
Panel Mount	Yes
Panel Mount Method	Flange

Electrical

Frequency	22 GHz
Impedance	50Ω
Power / Voltage	VOLTAGE: 335 Vrms@Sea Level

Material Info

Reference - Drawing Numbers

Sales Drawing	SD-73298-009
---------------	--------------



Series image - Reference only

EU ELV

Not Reviewed

EU RoHS

Not Reviewed

REACH SVHC

Not Reviewed

Halogen-Free

Status

Not Reviewed

For more information, please visit [Contact US](#)

China ROHS

Not Reviewed

ELV

Not Reviewed

RoHS Phthalates

Not Reviewed

Search Parts in this Series

[73298 Series](#)