

3-5/6 digits 5999 Counts Digital True RMS Multimeter

Item: MT-1280

- 1M drop protection
- 3-5/6 digits 5999 counts
- 0.5% best accuracy
- CAT III 1000V safety rated
- AC True-RMS for accurate measurements
- Large capacitance test to 2000uf
- Large backlit LCD display



DC Voltage	600mV/6V/60V/600V±(0.5%+3d), 1000V±(0.8%+10d)
True RMS AC Voltage	6V/60V/600V ±(0.8%+5d), 750V ±(1.2%+10d), Frequency response: (40~1000)Hz True RMS
DC Current	600uA/6mA/60mA±(0.8%+10d), 600mA ±(1.2%+8d), 20.00A±(2%+5d)
True RMS AC Current	60mA±(1%+5d) , 600mA(±2%+5d), 20.00A±(3%+10d), Frequency response: (40~1000)Hz True RMS
Resistance(Ω)	600Ω±(0.8%+5d) 6kΩ/60kΩ/600kΩ±(0.8%+3d), 60MΩ±(1%+25d), 600MΩ±(5%+10d)
Capacitance(μF)	9.999nF ±(5%+35d), 9.999nF~999.9uF ±(2.5%+20d) 999.9uF~2000uF ±(5%+35d)
Temperature(°C/°F)	-20°C~1000°C/ -4°F~1832°F±(1.0%+5d)
NCV Detection	Y
Continuity w/ Beeper	Y
Diode Test	Y
Transistor	Y
Data Hold	Y
Low Battery Indication	Y
Battery	9 Volt <i>Not Included</i>
Size	7.2 x 3.5 x 1.8 in.

Order Today! SalesSupport@EclipseTools.com

Eclipse Enterprises, Inc. ● Tel: 804.561.2610 ● Fax: 804.561.2642

13302 Chula Road, Amelia Court House, VA 23002 ● EclipseTools.com