ACDC Fan



San Ace 120AD

General Specifications

· Material ······ Frame: Plastics (Flammability: UL94V-0),

Impeller: Plastics (Flammability: UL94V-1)

· Motor Construction · · · · · Brushless DC motor

· Motor Protection System Burnout protection at locked rotor condition

· Dielectric Strength ······· 50/60 Hz, 1,500 VAC, 1 minute (between input terminal

and frame, and between sensor output and frame)

· Insulation Resistance \cdots 10M Ω or more at 500VDC megger (between lead

conductor and frame)

· Sound Pressure Level (SPL) ··· Expressed as the value at 1m from air inlet side

• Storage Temperature ----- -30°C to +75°C (Non-condensing)

* Do not weld directly onto AC input terminals.



120×120×38mm (Mass: 290g) 9AD type

Specifications

The model no. below has **ribs and no sensors**. For models without ribs, append "1" to the model no.

Model No.	Rated Voltage	Operating Voltage Range	Frequency ^(Note)	Rated Current	Rated Input	Rated Speed	Max. A	irflow	Max. Stat	tic Pressure	SPL	Operating Temperature	Expected Life
Widdel No.	[V]	[V]	[Hz]	[A]	[W]	[min ⁻¹]	[m³/min]	[CFM]	[Pa]	[inchH20]	[dB(A)]	[°C]	[h]
9AD1201H12	100 to 240	90 to 264	50/60	0.08	4.4	3,250	3.0	106	84	0.34	42	-20 to +75	60,000/60°C

Note: 50/60 Hz compatible.

The model no. below has ribs and low-speed sensors. For models without ribs, append "1" to the model no.

NA.	Model No.	Rated Voltage	Operating Voltage Range	Frequency ^(Note)	Rated Current	Rated Input	Rated Speed	Max. A	irflow	Max. Stat	tic Pressure	SPL	Operating Temperature	Expected Life
	Model No.	[V]	[V]	[Hz]	[A]	[W]	[min ⁻¹]	[m³/min]	[CFM]	[Pa]	[inchH ₂ 0]	[dB(A)]	[°C]	[h]
9	AD1201H1H	100 to 240	90 to 264	50/60	0.08	4.4	3,250	3.0	106	84	0.34	42	-20 to +75	60,000/60°C

Note: 50/60 Hz compatible.

Set Models

· The set models listed below can be ordered as a single order.

Set configuration items: Fan (without sensor), plug cord, finger guard, screws (with flat washer and spring washer), hex nuts, operation manual

	·	0			
Model Number to Order	Fan Model	Sensor Specifications	Plug Cord Model	Finger Guard Model	Mounting Screws
9U-9AD1201H12	9AD1201H12	Without sensorsensor	489-1635-L10 (Products compliant with Electrical Appliance and Material Safety Law, UL/CSA [c-UL] CERTIFIED)	109-019E	M4 screws (55 mm) x 4, Nuts x 4

Overheating protection function

Protection Functions:


If the fan blades are restricted, an overcurrent occurs and leads to a rise in the fan coil temperature. This can result in reduced performance, damage, or a fire. To prevent this from occurring, SANYO DENKI's fans incorporate an overheating protection function.


Burnout protection function at locked rotor condition

Current cutoff system (ACDC fan only)


If the fan blades are restricted, the coil current is cut off at regular cycles to prevent overheating of the coil. When the hindrance is removed, the fan restarts automatically.

without Sensor






with Low-speed sensor



Reference Dimensions of Mounting Holes and Vent Opening (unit: mm)





San Ace 120AD

120×120×38_{mm} (Mass: 290g)

Options (unit: mm)

Finger Guards

Color Surface treatment : Nickel-chrome plating (silver) Model: 109-019C


Outlet side

- **φ**148


Mass: 32g

Color Surface treatment: Nickel-chrome plating (silver) Model: 109-019E : 109-019K : Cation electropainting (black)

Inlet side, Outlet side





Resin Finger Guards



Resin Filter Kits


Model: 109-1000F13 (13PPI), 109-1000F20 (20PPI), 109-1000F30 (30PPI), 109-1000F40 (40PPI)





Plug Cord


(Products compliant with Electrical Appliance and Material Safety Law, UL/CSA [c-UL] CERTIFIED) UL FILE No. E43202 Model: 489-1635-L10/489-1635-L21




Model Power cord length (L) [mm] Mass [g] 489-1635-L10 1,000 489-1635-L21 2,100

Wiring Harness for Sensor

Model: 489-1636




Airflow - Static Pressure **Characteristics**




Wiring Diagram

without Sensor




with Low-speed sensor



Specifications for Low-speed Sensors


Model No.: 9AD1201H1H Output circuit: Open collector

VcE=+27.6 V DC MAX. Ic=10 mA MAX. [VcE (SAT) = 1.0 V MAX.]




Sensor scheme

Example 1: when steady running



Example 2: when the rotor is locked when the fan motor is turned on and released after the start-up delay time.



Startup delay: 18±3 sec. Detection delay: 3 sec. MAX. Trip point: 1,700 min-1